

User Manual — FURYCUBE Wireless Keyboard, White

FURYCUBE wireless keyboard — connection, function keys and everything you need

CONTENTS

- 1. General Presentation
- 2. Connection — 3 modes, up to 5 devices
- 3. Key Combinations (FN)
- 4. Specifications
- 5. What's in the Box
- 6. FAQ & Troubleshooting
- 7. Warranty & Support

1 General Presentation

The FURYCUBE IP98 PRO is a full-size (98-key) membrane keyboard with RGB backlight and three connection modes: 2.4G wireless, Bluetooth (up to 3 devices) and USB cable. It pairs with up to 5 devices and switches between them instantly. It has 19-key anti-ghosting, great for both office and gaming.

2 Connection — 3 modes, up to 5 devices

The keyboard connects in 3 ways and remembers up to 5 devices (1× 2.4G, 3× Bluetooth, 1× cable). Below, step by step:

- 1. TURN ON the keyboard with the ON/OFF switch (on the back).
- 2. 2.4G MODE (wireless, simplest): plug the small USB receiver into a computer port. Press FN + K and hold 2 seconds — the indicator turns green and connects automatically.
- 3. BLUETOOTH MODE (up to 3 devices — laptop, phone, tablet): 1) Press FN + J and hold 2 seconds — the indicator blinks blue (pairing). 2) On your phone/PC open Bluetooth settings and pick «FURYCUBE». 3) Done. For the 2nd device use FN + U, for the 3rd FN + I.
- 4. CABLE MODE: connect the USB-C cable to the computer and press FN + P. Works instantly.
- 5. SWITCH BETWEEN DEVICES (short press): FN + J / U / I = Bluetooth 1 / 2 / 3, FN + K = 2.4G, FN + P = cable.

FN + K	2.4G mode — hold 2s to pair (green indicator)
FN + J	Bluetooth 1 — short press = channel; hold 2s = pair (blue)
FN + U	Bluetooth 2 — short press = channel; hold 2s = pair
FN + I	Bluetooth 3 — short press = channel; hold 2s = pair
FN + P	USB cable mode (mode indicator off)

The Bluetooth pairing window is 60 seconds; if the indicator blinks over 60s without connecting, the keyboard turns off — turn it back on and retry. If a device won't reconnect, delete «FURYCUBE» from the Bluetooth list and pair again.

3 Key Combinations (FN)

Hold FN and press the indicated key. Media/system functions apply on Windows; some have a Mac equivalent.

FN + F1 / F2	Screen brightness – / +
FN + F3	Switch windows / Mission Control (Mac)
FN + F4	Microphone / Launchpad (Mac)
FN + F5	Media player / Siri (Mac)
FN + F6 / F7	Previous / next track
FN + F8	Play / Pause
FN + F9 / F10	Stop / Mute
FN + F11 / F12	Volume – / +
FN + Insert	Change lighting effect
FN + PgUp / PgDn	Backlight brightness + / –
FN + (+) / (–)	Effect speed + / –
FN + W	Swap WASD ↔ arrow keys
FN + N / FN + S	Switch to Windows / Mac mode
FN + Backspace	Backlight on / off
FN + Win (stânga)	Lock the Windows key (avoids accidental presses in games)

4 Specifications

Key type	Membrană (98 taste, full-size)
Connectivity	2.4G + Bluetooth 5.0 (×3) + USB
Simultaneous devices	până la 5 / up to 5
Lighting	RGB, 7 efecte / effects
Anti-ghosting	19 taste / keys
Power	5V, <240mA · acumulator reîncărcabil USB-C
Cable	USB Type-C, 1.5 m
Dimensions	385 × 136 × 35.5 mm
Compatibility	Windows XP/Vista/7/8/10, Mac

5 What's in the Box

- 1× FURYCUBE IP98 PRO keyboard
- 1× 2.4G USB receiver
- 1× USB Type-C charging cable
- 1× User manual

6 FAQ & Troubleshooting

Nu se conectează pe Bluetooth	Delete "FURYCUBE" from the device's Bluetooth list and re-pair (hold FN+J/U/I 2s). Pairing window is 60s.
Nu răspunde pe 2.4G	Check the USB receiver in the computer and that the mode is 2.4G (FN+K). On power-up the indicator blinks green.
Se oprește singură	It has auto sleep to save battery; press any key to wake. Charge it via USB-C.
Nu se aprinde iluminarea	Turn it on with FN+Backspace; adjust brightness with FN+PgUp.

7 Warranty & Support

The product is covered by warranty according to applicable law. For any question, fault or return, reach us anytime at support-netstat.ro — with contact details (e-mail, phone, WhatsApp), manuals, return conditions and warranty certificates. We reply fast and gladly.

Full support: support-netstat.ro · NETSTAT / FURYCUBE