

User Manual — FURYCUBE Wireless Mouse, White

FURYCUBE G11 mouse — 3 modes, DPI, buttons and troubleshooting

CONTENTS

- 1. General Presentation
- 2. Connection — 2.4G, Bluetooth, cable
- 3. Button Customization Software
- 4. DPI & Lighting
- 5. Specifications
- 6. What's in the Box
- 7. FAQ & Troubleshooting
- 8. Warranty & Support

1 General Presentation

The FURYCUBE G11 is an ultra-light (65g) gaming mouse with 6 buttons, an optical sensor up to 22000 DPI and three connection modes: 2.4G wireless, Bluetooth and cable. It connects to multiple devices and switches quickly between them. RGB lighting with several effects, USB Type-C rechargeable battery.

2 Connection — 2.4G, Bluetooth, cable

The FURYCUBE G11 has 3 connection modes. Select the mode with the switch under the mouse. Below, step by step, each mode:

- 1. CABLE MODE (simplest): plug the USB-C cable into the mouse and the other end into the computer. Works instantly, no setup. Note: to customize the buttons, the mouse MUST be connected by cable.
- 2. 2.4G MODE (wireless, recommended for gaming): 1) Take out the small USB receiver (in the slot under the mouse). 2) Plug it into a USB port. 3) Set the switch under the mouse to «2.4G» and turn the mouse on. On power-up the indicator blinks red for 3 seconds and connects automatically.
- 3. BLUETOOTH MODE (laptop / phone / tablet): 1) Set the switch to «BT». 2) Hold Left-click + Right-click + Scroll wheel TOGETHER for 3 seconds — the indicator blinks (pairing mode). 3) On your phone/PC open Bluetooth settings and pick «FURYCUBE / G11». 4) Done.
- 4. SWITCH BETWEEN 2 BLUETOOTH DEVICES: hold the DPI button for 3 seconds to switch from Bluetooth 1 to Bluetooth 2.

Intrare în modul asociere (pairing) — ca la W10	Hold Left-click + Right-click + Scroll wheel together for 3 seconds. The indicator starts blinking = you're in pairing; then select the device.
Buton DPI / Bluetooth	Hold 3s to switch between Bluetooth 1 and Bluetooth 2
Stânga + Mijloc (roțiță)	2.4G mode — hold 3s to enter pairing
Stânga + Mijloc + Dreapta	Bluetooth mode — hold 3s to pair with a new device
Dreapta + buton Înainte	Change lighting effect (cycle: single, neon, 7-color, mixed, marquee, off)

For Bluetooth: after entering pairing (indicator blinks), open Bluetooth on your phone/PC and pick "FURYCUBE / G11". If you change the computer or adapter, pair again.

3 Button Customization Software

The FURYCUBE G11 mouse buttons can be customized (button remap, macros, DPI levels, lighting effects) in two ways, depending on your operating system:

 Windows: download and run the FuryCube.exe app — it's the native Windows application. Download: <https://support-netstat.ro/software/FuryCube.exe> . Open it and configure the mouse directly.

 macOS: use the web version at <https://www.bk-gmice.com/#Furycube/factoryG11>. When it opens, the browser may show a red warning page («not secure») — this is normal and safe: click «Advanced» → «Continue to site», then click «Connect» and select the mouse.

IMPORTANT: button customization works **ONLY** when the mouse is connected by **CABLE** — not over Bluetooth or 2.4G. On Mac you can connect the mouse through a USB docking station or hub; if you don't have one, use a cable with Type-C on both ends, straight into the Mac's USB-C port (for example the iPhone cable).

4 DPI & Lighting

The DPI button (short press) cycles the sensitivity levels, up to 22000 DPI. Lighting effects change with Right + Forward button and can be fine-tuned in the dedicated software.

5 Specifications

Sensor / DPI	optic, până la 22000 DPI
Buttons	6 butoane
Weight	~65 g (ultra-ușor)
Connectivity	2.4G + Bluetooth (×2) + cablu
Lighting	RGB, mai multe efecte
Battery	400mAh, reîncărcabilă USB-C
2.4G range	~10 m
Cable	USB Type-C
Compatibility	Windows, macOS, Android

6 What's in the Box

- 1× FURYCUBE G11 mouse (3 modes)
- 1× 2.4G USB receiver
- 1× USB Type-C cable
- 1× User manual

7 FAQ & Troubleshooting

Nu merge pe Bluetooth	Use a quality Bluetooth adapter; make sure Bluetooth is on; delete the device from the list and re-pair. After changing PC/adaptor, pair again.
Nu merge pe 2.4G	Switch to 2.4G mode — the red indicator lights for 3 seconds. Check the USB receiver.
Cursor imprecis / sacadat	Use it within 10 m and avoid glossy/transparent surfaces; a mousepad is ideal.
Cum îl încarc?	Via the included USB Type-C cable; you can use the mouse while charging.

8 Warranty & Support

The product is covered by warranty according to applicable law. For any question, fault or return, reach us anytime at support-netstat.ro — with contact details (e-mail, phone, WhatsApp), manuals, return conditions and warranty certificates. We reply fast and gladly.

Full support: support-netstat.ro · NETSTAT / FURYCUBE